

1. Connect red test lead to "V Ω mA" jack. Black lead to "COM" jack.
2. Set RANGE switch to desired DCV position. If the voltage to be measured is not known beforehand, set switch to the highest range and reduce it until satisfactory reading is obtained.
3. Connect test leads to device or circuit being measured.
4. Turn on power of the device or circuit being measured, voltage value will appear on Digital Display along with the voltage polarity.

AC VOLTAGE MEASUREMENT

1. Red lead to "V Ω mA". Black lead to "COM".
2. RANGE switch to desired ACV position.
3. Connect test leads to device or circuit being tested.
4. Read voltage value on Digital Display.

DC CURRENT MEASUREMENT


1. Red lead to "V Ω mA". Black lead to "COM". (For measurements between 200mA and 10A connect red lead to "10A" jack with fully depressed.)
2. RANGE switch to desired DCA position.
3. Open the circuit to be measured, and connect test leads IN SERIES with the load in which current is to be measured.
4. Read current value on Digital Display.

RESISTANCE MEASUREMENT

1. Red lead to "V Ω mA". Black lead to "COM".
2. RANGE switch to desired Ω Position.
3. If the resistance being measured is connected to a circuit, turn off power and discharge all capacitors before measurement.

4. Connect test leads to circuit being measured.
5. Read resistance value on Digital Display.

DIODE MEASUREMENT

1. Red lead to "V Ω mA". Black lead to "COM".
2. RANGE switch to  position.

3. Connect the red test lead to the anode of the diode to be measured and black test lead to cathode.
4. The forward voltage drop in mV will be displayed. If the diode is reversed, figure "1" will be shown.

TRANSISTOR hFE MEASUREMENT

1. RANGE switch to the hFE position.
2. Determine whether the transistor is NPN or PNP type and locate the Emitter, Base and Collector leads, Insert the leads into the proper holes of the hFE Socket on the front panel.
3. The meter will display the approximate hFE value at the condition of base current 10 μ A and VCE 2.8V.


TEMPERATURE MEASUREMENT

1. Connect the k type thermoelectric couple to "V Ω mA" and "COM" jacks.
2. RANGE switch to TEMP position.
3. The display will read the Temperature value $^{\circ}$ C.

AUDIBLE CONTINUITY TEST

1. Red lead to "V Ω mA". Black lead to "COM".
2. RANGE switch to \cdot) position.
3. Connect test leads to two points of circuit to be tested. If the resistance is lower than 100 ohm, buzzer will sound.

TEST SIGNAL USE

1. RANGE switch to  position.
2. A test signal (50Hz for 832, 837 and 1000Hz for 838) appears between "V Ω mA" and "COM" jacks. The output voltage is approx 5V p-p with 50k ohm impedance.

BATTERY AND FUSE REPLACEMENT

Fuse rarely need replacement and blow almost always as a result

of operator error.

If "BAT" appears on display, it indicates that the battery should be replaced.

To replace battery & Fuse (200mA/250V) remove the 2 screws in the bottom of the case. Simply remove the old, and replace with a new one. Be careful to observe polarity.

83L SERIES (DMM with flashlight , 2 IN 1) .

1. Set switch button up, flashlight and back lit display will turn on.
2. Set the switch down, back lit display turn on only.

CAUTION

Before attempting to open the case of the instrument, be sure to disconnect test leads from any energized circuits to avoid shock hazard.

ACCESSORIES

- Operator's instruction manual
- Set of test leads
- Gift box
- K type thermoelectric couple (837, 838, only)
- 9 volt battery, NEDA 1604 6F22 TYPE (Optional).
- "AA"size batteries (83L series only)

OPERATOR'S INSTRUCTION MANUAL




Model ATD 5536

MINI DIGITAL MULTIMETER



WARNING

READ AND UNDERSTAND THIS MANUAL BEFORE USING THE INSTRUMENT.
Failure to understand and comply with the WARNINGS and operating instructions can result in serious or fatal injuries and/or property damage.



GENERAL

83 instruments are a series of compact pocket-sized 3½ digit multimeters for measuring DC and ac voltage, DC current, resistance and diode. Some of those also provide temperature, transistor measurement and audible continuity test function or can be used as a signal generator (see table). Full range overload protection and low battery voltage indication are provided. they are ideal instruments for use in fields, such as laboratory, workshop, hobby and home applications.

83 83L series multimeters

Model	DCV	ACV	DCA	Ω	▶	BAT	HFE)))	TEMP
830B
831
832
832B
833
837
838

FRONT PANEL DESCRIPTION

1. FUNCTION AND RANGE SWITCH

This switch is used to select the function and desired range as well as to turn on the instrument.

To extend the life of this battery, the switch should be in the "OFF" position when the instrument is not in use.

2. DISPLAY

3½ digit, 7 segment, 0.5" high LCD.

3. "Common" JACK

Plug in connector for black (negative) test lead.

4. "V Ω mA" JACK

Plug in connector for red (Positive) test lead for all voltage

and resistance and current (except 10A) measurements.

5. "10A" JACK

Plug in connector for red (positive) test lead for 10A measurement.

SPECIFICATIONS

Accuracies are guaranteed for 1 year, 23°C±5°C, less than 75% RH.

DC VOLTAGE

RANGE	RESOLUTION	ACCURACY
200mV	100µV	±0.5% of rdg±2D
2000mV	1mV	±0.5% of rdg±2D
20V	10mV	±0.5% of rdg±2D
200V	100mV	±0.5% of rdg±2D
1000V	1V	±0.5% of rdg±2D

OVERLOAD PROTECTION: 220V rms AC for 200mV range and 1000V DC or 750V rms AC for other ranges.

AC VOLTAGE

RANGE	RESOLUTION	ACCURACY
200V	100mV	±1.2% of rdg±10D
750V	1V	±1.2% of rdg±10D

OVERLOAD PROTECTION: 1000V DC or 750Vrms for all ranges.

RESPONSE: Average responding, calibrated in rms of a sine wave.

FREQUENCY RANGE: 45Hz-450Hz.

DC CURRENT

RANGE	RESOLUTION	ACCURACY
200µA 100nA		±1% of rdg±2D
2000µA	1µA	±1% of rdg±2D
20mA	10µA	±1% of rdg±2D
200mA	100µA	±1.2% of rdg±2D
10A	10mA	±2.0% of rdg±2D

OVERLOAD PROTECTION: 200mA 250V fuse

(10A range unfused).

MEASURING VOLTAGE DROP: 200mV.

RESISTANCE

RANGE	RESOLUTION	ACCURACY
200ohm	100m ohm	±0.8% of rdg±2D
2000 ohm	1 ohm	±0.8% of rdg±2D
20k ohm	10 ohm	±0.8% of rdg±2D
200k ohm	100 ohm	±0.8% of rdg±2D
2000k ohm	1k ohm	±1.0% of rdg±2D
20M ohm	10k ohm	±1.5% of rdg±3D

MAXIMUM OPEN CIRCUIT VOLTAGE: 2.8V.

OVERLOAD PROTECTION: 15 seconds maximum 220V rms on all ranges.

AUDIBLE CONTINUITY

RANGE DESCRIPTION

))) Built-in buzzer sounds if resistance is less than 100 ohm

OVERLOAD PROTECTION: 15 seconds maximum 220V rms Sounds alarm.

TEMPERATURE (K TYPE PROBE)

RANGE	RESOLUTION	ACCURACY
-20°C to 1370°C	1°C	±3% ±2D(up to 150°C) ±3% of rdg (over 150°C)

OVERLOAD PROTECTION: 220Vrms AC.

OPERATING INSTRUCTIONS

WARNING

1. To avoid electrical shock hazard and/or damage of the instrument, do not measure voltages that might exceed 500V above earth ground.

2. Before the use of instrument, inspect test leads, connectors and probes for cracks, breaks, or crazes in the insulation.

DC VOLTAGE MEASUREMENT