




MULTIMATCH 3

03.5653/03.5653AU/03.5653UK/03.5653US



ALL DAYLIGHT - 5 step

Operating

5-step dimmer function and option to change between 5 colour temperatures (2500K-6500K).

Press and hold power button 2 sec. to change between CCT and light output level.



Bluetooth
Light control app



INCL. SPS BATTERY 4Ah
ITEM NO. 03.6003



Power bank



Ultra high CRI+
COB LED



450-4500lux
@0.5m



3000lm@100%
2250lm@75%
1500lm@50%
750lm@25%/300lm@10%



2500K/3500K/4500K
/5500K/6500K



CRI 96+



11.1V / 4000 mAh
Backup:
7.4V/1000mAh



1.5-15h
Backup:
2h@10%/300lm



1.5h@80%



Max 30W



-10° to +40° C



IK07



IP67

Above specifications apply to the work light only



240x230x104 mm



1.97 kg



INCL. SPS CHARGER 35W
ITEM NO. 03.6006
INPUT: 100-240V AC 50/60HZ
OUTPUT: 12.6V DC 2.8A
CABLE: 5m 2x0.75mm² H05RN-F

WARNING-Risk of fire
Minimum distance from
lighted objects 0.1m



MULTIMATCH 3

WARNING

- Always respect applicable legislation for working with electrical equipment in order to reduce the risk of accidents
- Avoid looking directly into the beam of light, as this will result in dazzling
- Do not use the lamp near a naked flame
- Protect the mains cable from oil, heat and sharp edges
- The light source of this luminaire is not replaceable; when the light source reaches its end of life the whole luminaire shall be replaced
- Luminaire is only suitable for direct mounting on non-combustible surfaces.
- The external flexible cable or cord of this luminaire cannot be replaced; if the cord is damaged, the luminaire shall be destroyed
- If the lamp is disconnected from mains and the battery is discharged, push the power button to enable internal back up battery. 10% LED will blink to indicate back up mode
- The red charging indicator lights up during charging
- The green charging indicator lights up when charging is completed.

The process to delete the pin code is:

- Turn on the Bluetooth function
- Press the Bluetooth button for 10 second
- The pin code is reset

Integrated BLUETOOTH light control

- Turn lamp on/off or adjust lamp output
- Connect up to 4 lamps together
- Adjust color temperature in steps from 2500k-6500k
- Assign pincode to prevent other users from controlling the lamp

Compliant with iPhone 5 or higher / Android 5.0 or higher. Go to iTunes App Store / Download the app from our website

Power bank

- Built-in power bank with USB outlet to charge mobile devices
- Output: 5V, 1A

The power bank will automatically shut down when the battery pack is discharged or removed. When using the power bank while the power supply is connected, the luminous output will be reduced to 75%.



Discarded electrical products must not be disposed of together with household waste. Please use recycling facilities. Ask your local authority or retailer for advice on recycling.

- The battery must be removed from the device before it is broken up
- The device must be disconnected from the mains when the battery is removed
- Please dispose of the battery safely

Discover other portable work lights on our website.