

## NOVA 4 SPS

03.6000/03.6000AU/03.6000UK



**Bluetooth®**  
Light control app



INCL. SPS BATTERY 4Ah  
ITEM NO. 03.6003



Power bank



High efficiency  
COB LED



175lm/W



600-6000lux  
@0.5m



4000lm@100%  
3000lm@75%  
2000lm@50%  
1000lm@25%/400lm@10%



11.1V / 4000 mAh  
Backup:  
7.4V/1000mAh



1.5-15h  
Backup:  
2.5h@10%/400lm



1.5h@80%



Max 30W



-10° to +40° C



IK07



IP67



240x230x104 mm



1.97 kg

Above specifications apply to the work light only

INCL. SPS CHARGER 35W  
ITEM NO. 03.6006  
INPUT: 100-240V AC 50/60HZ  
OUTPUT: 12.6V DC 2.8A  
CABLE: 5m 2x0.75mm² H05RN-F

Work light specifications



## WARNING / BATTERY TIPS

- Always respect applicable legislation for working with electrical equipment in order to reduce the risk of accidents
- Avoid looking directly into the beam of light, as this will result in dazzling
- Do not use the lamp near a naked flame
- Protect the mains cable from oil, heat and sharp edges
- Only use SCANGRIP SPS battery packs. Internal backup battery must be replaced with an original SCANGRIP battery
- Do not leave the battery flat, as this could render it INCAPABLE of being charged again
- The light source of this luminaire is not replaceable; when the light source reaches its end of life the whole luminaire shall be replaced
- Luminaire is only suitable for direct mounting on non-combustible surfaces
- The luminaire is designed to work with all SCANGRIP SPS battery packs. Likewise, the battery chargers can be used to power the luminaire
- If the lamp is disconnected from mains and the battery is discharged, push the power button to enable internal back up battery. 10% LED will blink to indicate back up mode
- The red charging indicator lights up during charging
- The green charging indicator lights up when charging is completed

## The process to delete the pin code is:

- Turn on the Bluetooth function
- Press the Bluetooth button for 10 second
- The pin code is reset

## Integrated BLUETOOTH light control

- Turn lamp on/off or adjust lamp output
- Connect up to 4 lamps together
- Assign pincode to prevent other users from controlling the lamp

Compliant with iPhone 5 or higher / Android 5.0 or higher. Go to iTunes App Store / Download the app from our website

## Power bank

- Built-in power bank with USB outlet to charge mobile devices
- Output: 5V, 1A

The power bank will automatically shut down when the battery pack is discharged or removed. When using the power bank while the power supply is connected, the luminous output will be reduced to 75%.



Discarded electrical products must not be disposed of together with household waste. Please use recycling facilities. Ask your local authority or retailer for advice on recycling.

- The battery must be removed from the device before it is broken up
- The device must be disconnected from the mains when the battery is removed
- Please dispose of the battery safely