

How-to-operate the BLUETOOTH LIGHT CONTROL of the MULTIMATCH series

Units screen

SETTINGS MENU (Menu icon)

List of available lamps

CONNECTION INDICATOR: ● connected ○ disconnected

BATTERY INDICATOR:

- Replace/recharge
- Battery full
- Power supply connected
- Internal battery backup

PINCODE STATUS: 🔓 Unlocked 🔒 Locked - pincode required

REFRESH BUTTON: Press to refresh list or swipe down on page (Refresh icon)

Units | Control

Control Press "control" button to select connected lamp to control

Control screen

Current lamp name

% LUMEN INDICATOR: Shows the current lumen level (10%)

K CCT INDICATOR: Shows the current colour temperature (2500K)

BATTERY INDICATOR:

- Replace/recharge
- Battery full
- Power supply connected
- Internal battery backup

>1h **TIME LEFT:** Shows the remaining operating time at current battery level

CCT SLIDER: CCT regulation (6500K, 5500K, 4500K, 3500K, 2500K)

LUMEN SLIDER: Lumen level regulation (100%, 75%, 50%, 25%, 10%)
Slide or press directly on the number

RENAME: Press to rename lamp (Rename icon)

PINCODE: Press to assign/clear pincode on lamp (Lock icon)

Units | On/off

Units Press "Units" to return to units page

On/off ON/OFF BUTTON: Press to turn the lamp on/off