



### **200966** 3500W Dual Fuel Portable Generator

### **A** WARNING:

Read the ENTIRE operator's manual to become familiar with the features of the product before operating.

Failure to operate the product correctly can result in damage to the product, personal property and cause serious injury or even death.





# 1.

2.

**Open shipping carton.** Assembly > Unpacking



**Remove brackets.** Assembly > Remove Shipping Support Brackets.



Attach wheel kit. Assembly > Install Wheel Kit
Attach wheel kit. Assembly > Install Wheel Kit
Image: Attach wheel kit. Assembly > Install Wheel Kit

**Connect the battery.** Assembly > Connect the Battery.

Cut cable tie on each side of battery connector. Push two halves of battery connector together tightly.





Add oil. Assembly > Add Engine Oil. Recommended: 10W-30, up to 20.3 fl. oz. (600 ml) D0 N0T overfill.



## Start Up 4



Move the **choke lever** to the "CHOKE" position.



# Start Up 🗲



### Gasoline

#### Electric Start

Press and hold the ignition switch to the "START" position.
 Move the choke lever to the "RUN" position.



#### Manual Start

- 1. Pull the starter cord.
- 2. Move the choke lever to the "RUN" position.





#### **Manual Start**

- 1. Pull the starter cord 2-3 times until you feel some combustion pulses.
- 2. Move the choke lever to the "RUN" position.
- 3. Pull the starter cord.



**Plug in.** *D* Operation > Connecting Electrical Loads.

