



6" Random Orbit Sander

Model B06050J

Fine or Fast Finish with 2-Mode Selection



PERFORMANCE

6.6 AMP motor rotates pad 1,600 - 6,800 OPM for smooth finish sanding



ACCURACY

2-mode switch for "random orbit" and "random orbit with forced rotation"



SPEED

Uses hook-and-loop abrasive discs for quick changes



COMFORT

Ergonomically designed barrel grip and side handle



HOOK-AND-LOOP



FEATURES

- Convenient 2-mode switch for "random orbit" and "random orbit with forced rotation" action
- Variable speed control dial (1,600 - 6,800 OPM) to match the speed to the application
- Ergonomically designed barrel grip and side handle for increased comfort
- 7/32" orbit diameter provides a swirl-free finish
- "Tool-less" backing pad change enables quick pad change to meet application
- Efficient through-the-pad dust collection system with built-in dust port for a cleaner work environment
- Lock-on slide trigger switch for added convenience of continuous operation
- Uses quick-change 6" hook-and-loop abrasive discs for fast and easy installation
- Removable pad protector protects work surface and backing pad

SPECIFICATIONS

Pad size (round)	6"
Abrasive disc size	6"
Orbits Per Minute (variable speed)	1,600 - 6,800 OPM
Orbit diameter	7/32"
AMPS	6.6
Vibration	5 m/s ²
Dimensions (LxWxH)	13" x 6-1/8" x 5-3/4"
Net weight	5.7 lbs.
UPC code	088381-804585

STANDARD EQUIPMENT

- 6" Round abrasive disc, hook-and-loop, 120 Grit (794610-0-1)
- 6" Round backing pad, hook-and-loop (197314-7)
- Dust nozzle (143326-8)
- Pad protector (456127-8)
- Side Handle (153489-2)
- Interlocking case, large (197212-5)

OPTIONAL ACCESSORIES

- 6" Round backing pad, hook-and-loop, available for: (coarse sanding, general purpose, fine sanding, polishing)
- 5" Round backing pad, hook-and-loop (polishing)
- 6" Wool bonnet, hook-and-loop (polishing)
- 6" Round abrasive disc, hook-and-loop, 10/pk – available in: (40, 60, 80, 120, 240 Grit)